

# dared

Preliminary  
Product Information

## Jupiter Full Balanced Vacuum Tube Stereo Pre-Amplifier



Back



Remote Control

### Specifications:

Input Impedance:

Line 1, 2, 3: 100k, Balanced: 100k, Phono: 47k/47pf

Output Impedance:

Unbalanced: 10kohms, Balanced. 600ohms

Input: Line 1, Line 2, Line 3, Balanced, Phono

Output Voltage: 10Vrms

Frequency Response: 10Hz-50kHz

Dimensions: 430x305x70mm / 16.93"x12.01"x2.76" (WxDxH)

Weight: 11kg / 24.25lbs

S/N Ratio: 92dB

Remote Control

Output: RCA x2, Blanced x2

Tubes: 12AX7 x2, 12AT7 x1, EL84 x1

Max. Power Consumption: 50W

Input Voltage: 110-120VAC, 220-240VAC

### Dared Audio International:

Luen Hing Electrical (HK) Limited

Address: G/F., 152 Apliu Street, Shamshuipo, Kowloon, Hong Kong

Tel +852 2728 8745 Fax: +852 2729 2962

Email: [worldsales@dared.com.hk](mailto:worldsales@dared.com.hk)

[www.dared.com.hk](http://www.dared.com.hk)